



PNNL-29494 SW 2.6.0

# SpecFIDLER User Manual

## Software Version 2.6.0

September 2024

Mitchell J Myjak  
Scott J Morris  
Jesse A Willett



Prepared for the U.S. Department of Energy  
under Contract DE-AC05-76RL01830

UNCLASSIFIED

## DISCLAIMER

This report was prepared as an account of work sponsored by an agency of the United States Government. Neither the United States Government nor any agency thereof, nor Battelle Memorial Institute, nor any of their employees, makes **any warranty, express or implied, or assumes any legal liability or responsibility for the accuracy, completeness, or usefulness of any information, apparatus, product, or process disclosed, or represents that its use would not infringe privately owned rights.** Reference herein to any specific commercial product, process, or service by trade name, trademark, manufacturer, or otherwise does not necessarily constitute or imply its endorsement, recommendation, or favoring by the United States Government or any agency thereof, or Battelle Memorial Institute. The views and opinions of authors expressed herein do not necessarily state or reflect those of the United States Government or any agency thereof.

PACIFIC NORTHWEST NATIONAL LABORATORY  
*operated by*  
BATTELLE  
*for the*  
UNITED STATES DEPARTMENT OF ENERGY  
*under Contract DE-AC05-76RL01830*

Printed in the United States of America

Available to DOE and DOE contractors from  
the Office of Scientific and Technical Information,  
P.O. Box 62, Oak Ridge, TN 37831-0062  
[www.osti.gov](http://www.osti.gov)  
ph: (865) 576-8401  
fox: (865) 576-5728  
email: [reports@osti.gov](mailto:reports@osti.gov)

Available to the public from the National Technical Information Service  
5301 Shawnee Rd., Alexandria, VA 22312  
ph: (800) 553-NTIS (6847)  
or (703) 605-6000  
email: [info@ntis.gov](mailto:info@ntis.gov)  
Online ordering: <http://www.ntis.gov>

# **SpecFIDLER User Manual**

Software Version 2.6.0

September 2024

Mitchell J Myjak  
Scott J Morris  
Jesse A Willett

Prepared for  
the U.S. Department of Energy  
under Contract DE-AC05-76RL01830

Pacific Northwest National Laboratory  
Richland, Washington 99354

**UNCLASSIFIED**

## Executive Summary

The Spectroscopic Field Instrument for Detection of Low Energy Radiation (SpecFIDLER) allows response teams to detect and quantify plutonium contamination on the ground. Notional scenarios include dispersion from a weapon accident, or the launch failure of a space probe containing a radioisotope thermoelectric generator. Unlike other instruments, the thin-window sodium iodide detector is sensitive to the low-energy gamma rays emitted by plutonium isotopes. The system supports both mobile survey as well as stationary sampling.

This manual provides information about installing, maintaining, and troubleshooting the SpecFIDLER. The scope of this document includes the physical hardware, software for data acquisition, and algorithms for data analysis. Recent changes to the software and algorithms aim to streamline the operation of the system.

## Acronyms and Abbreviations

γpm	gammas per minute
cpm	counts per minute
DFM	Digital Field Monitoring
dpm	disintegrations per minute
MDA	minimum detectable activity
MT	material type
Nal:TI	thallium-doped sodium iodide
ROI	region of interest
RSL	Remote Sensing Laboratory
SNL	Sandia National Laboratories
SpecFIDLER	Spectroscopic Field Instrument for Detection of Low Energy Radiation
USB	Universal Serial Bus

## Contents

Executive Summary .....	ii
Acronyms and Abbreviations.....	iii
1.0 Introduction .....	1
2.0 Setup.....	2
2.1 Assembly .....	2
2.2 Disassembly .....	7
2.3 Transportation.....	8
2.4 Software Installation.....	9
3.0 Operation .....	11
3.1 General Settings .....	12
3.2 Mobile Survey .....	13
3.3 Streaming to AVID .....	15
3.4 Stationary Sampling.....	15
3.5 Source Term .....	17
3.6 Nuclide Analysis .....	19
3.7 Batch Analysis .....	21
3.8 Shutdown.....	23
4.0 Calibration .....	24
4.1 Voltage Calibration.....	24
4.2 Energy Calibration .....	25
4.3 Efficiency Calibration .....	27
5.0 Maintenance.....	29
5.1 Version Information.....	29
5.2 Upgrading from Previous Versions.....	29
5.3 Replacing usbBase .....	29
5.4 Log Files .....	30
6.0 Algorithms .....	31
6.1 Background Subtraction.....	31
6.2 Energy Calibration .....	31
6.3 Efficiency Calibration .....	32
6.4 Nuclide Analysis .....	33
7.0 References.....	35
Appendix A – Configuration File .....	36
Appendix B – Settings File .....	37
Appendix C – Licensing .....	44

## Figures

Figure 1.	Components of the SpecFIDLER .....	1
Figure 2.	Handle locations. ....	2
Figure 3.	Extending the top handle. ....	3
Figure 4.	Extending the legs. ....	4
Figure 5.	Beryllium window. ....	5
Figure 6.	USB connections. ....	6
Figure 7.	Detector leg removal, viewed from top of instrument looking downward. ....	7
Figure 8.	SpecFIDLER setup wizard. ....	9
Figure 9.	Zadig configuration. ....	10
Figure 10.	Main screen showing various tabs. ....	11
Figure 11.	<b>Settings</b> tab.....	12
Figure 12.	<b>Rate</b> tab.....	13
Figure 13.	<b>Spectra</b> tab.....	16
Figure 14.	<b>Source term</b> tab.....	18
Figure 15.	<b>Analysis</b> tab.....	19
Figure 16.	<b>Batch</b> tab.....	22
Figure 17.	Am-241 spectrum with good high voltage setting. ....	24
Figure 18.	<b>Energy Cal</b> tab. ....	26
Figure 19.	<b>Efficiency Cal</b> tab. ....	27

## 1.0 Introduction

The Spectroscopic Field Instrument for Detection of Low Energy Radiation (SpecFIDLER) allows response teams to detect and quantify plutonium contamination on the ground. The system contains the following components:

- Thallium-doped sodium iodide (NaI:Ti) detector with a thin beryllium window.
- Bridgeport Instruments usbBase for detector readout.
- Enclosure containing a rechargeable battery and Universal Serial Bus (USB) hub.
- Battery power switch and power indicator on the outside of the enclosure.
- USB cables to the detector and an external tablet computer.

Figure 1 depicts the components of the SpecFIDLER in their representative setup. The tablet computer may be mounted on the back side of the unit or carried separately.




Figure 1. Components of the SpecFIDLER.

The remainder of this manual describes the setup, operation, calibration, and maintenance of the SpecFIDLER. The appendices provide additional information about the configuration file and settings file for advanced users. Also included are the licenses for the libraries used by the software.

## 2.0 Setup

This section describes how to assemble the SpecFIDLER for deployment, disassemble the unit for storage, transport the unit to another location, and install the software on the tablet.

### 2.1 Assembly

To assemble the SpecFIDLER, follow the procedure below.

1. Open the shipping container and remove the Velcro hold-down strap. Grasp both handles (Figure 2) and lift the unit straight out.




Figure 2. Handle locations.

2. Extend the top handle by pulling the pins (Figure 3) and lifting straight up until the desired height is reached. Use the pins to lock the handle into place.




Figure 3. Extending the top handle.

3. Loosen the leg locks (Figure 4) and extend the legs down. Swing the legs out by pulling the pin, swinging the leg, and inserting into the second hole. Lock the legs in place. Consider tying rubber gloves onto each leg to prevent contamination.




Figure 4. Extending the legs.

4. Carefully remove the cover from the fragile beryllium window (Figure 5), ensuring that it is not scratched or damaged in any way.




Figure 5. Beryllium window.

**NOTE:** Beryllium is a potentially hazardous material that is controlled by most industrial hygiene groups. However, solid beryllium metal, alloys, ceramic objects, and finished products, such as the detector window used in the SpecFIDLER instrument, pose no special health risks unless their use or handling generates airborne aerosols or surface contamination. For example, if the window gets scratched, scraps of beryllium may become airborne and inhaled or land on exposed skin. Exposure can occur by inhaling particles from aerosols, by getting loose particles on the skin, or by cutting the skin with sharp edges of materials. Damaged beryllium objects should be handled with care to avoid injury from sharp pieces and dispersal of beryllium dust.

5. Ensure that the USB cables are connected properly to the enclosure (Figure 6). However, do not connect the USB cable to the tablet yet.




Figure 6. USB connections.

6. Charge the lithium-ion battery if necessary.
7. Install the lithium-ion battery inside the enclosure. Ensure that both battery contacts make a good connection; unfortunately, the battery holder is very tight.
8. Turn on the power using the switch and verify that the red light is illuminated. If not, double-check the battery connections.
9. Connect the USB cable to the tablet. The tablet may be placed in the pocket on the frame behind the detector.
10. Finally, start the software, as described in Section 3.1.

**NOTE:** If the tablet is connected to the SpecFIDLER before turning on the power switch, then the tablet will supply power rather than the internal battery. This configuration works fine but will shorten the tablet's battery life. The red light is illuminated in either case.

## 2.2 Disassembly

Disassembly is the reverse of assembly:

1. Shut down the software, as described in Section 3.8.
2. Unplug the tablet and turn off the power using the switch.
3. Remove the lithium-ion battery.
4. Place the cover back onto the detector to protect the fragile beryllium window.
5. Retract the top handle and the legs.
6. Finally, place the unit back into the storage container.

If the legs become contaminated, they may be removed. Loosen the leg locks, twist the legs such that the long end of the pin faces the center of the instrument (Figure 7), and drop the legs down through the clamps.




Figure 7. Detector leg removal, viewed from top of instrument looking downward.

**NOTE:** The long side of the pin must face away from the threads on the leg lock. Otherwise, the pin will not fit through the hole.

## 2.3 Transportation

Often it is necessary to load the SpecFIDLER into a vehicle and transport it to another measurement location. For shorter trips, the following steps are recommended:

1. Remove any protective gloves from the legs to avoid contaminating the vehicle.
2. Place the cover back onto the detector to avoid damaging the beryllium window.
3. Lay the unit on its side, orienting the unit so that other objects do not contact the detector. Secure the unit so that it does not slide around.

For longer trips, consider packing the unit back into the storage container.

**NOTE:** Protect the fragile beryllium window at all times.

## 2.4 Software Installation

The SpecFIDLER software is integrated with the Digital Field Monitoring (DFM) software on the Consequence Management tablet. Normally, the tablets come preloaded with all the requisite programs and utilities. However, follow the procedure below if it is necessary to install, upgrade, or repair the SpecFIDLER software:

1. The installation package consists of two files: **setup.exe** and **Installer.msi**. Copy these files to a temporary folder on the tablet.
2. Uninstall the existing SpecFIDLER software if necessary. The data and configuration files are retained.

**NOTE:** All versions of the SpecFIDLER software must be uninstalled first.

3. Next, install the SpecFIDLER software. Locate the temporary folder and run **setup.exe**. Click **Next** and select the installation folder (Figure 8). Click **Next** two more times. If a dialog appears asking to confirm security access to the installer, select **Yes**.




Figure 8. SpecFIDLER setup wizard.

**NOTE:** The **eM\_DLL.dll** file in the installation folder is a custom version of the Bridgeport Instruments library. It has bug fixes and additional features applied. Do not replace this file with the stock version provided by Bridgeport Instruments; otherwise, runtime errors will occur.

4. Use the procedure in Section 2.1 to assemble the SpecFIDLER and connect the USB cable to the tablet.
5. Associate the Bridgeport Instruments usbBase with the correct driver. Run **Zadig** from the **SpecFIDLER** folder in the Start Menu. Select the **eMorpho** device from the drop-down. (If this option does not appear, select **Options->List All Devices** from the menu.) Change the driver to **WinUSB** and click **Install Driver** (Figure 9).




Figure 9. Zadig configuration.

**NOTE:** The new version of the software requires the **WinUSB** driver rather than **lib-usbwin32**. The **libusbK** driver is also acceptable. The software will fail if the correct driver is not associated with the usbBase.

6. Use the procedure in Section 5.1 if upgrading from an older version of the software to version 2.

## 3.0 Operation

The SpecFIDLER software is called by the DFM software on the tablet. Click the **Launch SpecFIDLER** button to begin.

The tabs along the right side of the main screen (Figure 10) switch between various modes. The **Rate** and **Spectra** tabs acquire data from the detector. The **Source term** tab defines the mixture of nuclides in the source term. The **Analysis** tab computes the nuclide quantities. The **Batch** tab reprocesses historical data. The **Energy cal** tab and **Efficiency cal** tabs handle the detector calibration. Finally, the **Settings** tab allows users to adjust and save parameters.




Figure 10. Main screen showing various tabs.

Note that the **Source term**, **Energy cal**, and **Efficiency cal** tabs display the *present* source term and detector calibrations. The **Settings** tab specifies the *default* parameters. This distinction should become clear in the subsequent discussion.

The remainder of this section describes how to operate the SpecFIDLER for both mobile survey and stationary sampling. These procedures assume that the detector has already been calibrated. Section 4.0 describes the calibration process.

### 3.1 General Settings

Before acquiring data for the first time, take a moment to examine the **Settings** tab (Figure 11). The various parameters configure the display, specify the default background and detector calibrations, and define the available source terms. All parameters and tables are fully editable. Rather than describing each parameter here, the following sections reference the parameters that pertain to the functions at hand.




Figure 11. **Settings** tab.

All parameters are stored in a file named **settings.xml** in the SpecFIDLER working directory (**c:\fidler** by default). Click **Save** to save the parameters to the settings file. Alternatively, click **Revert** to discard all changes and reload the settings file. The software will also prompt whether to save changes on exit.

To transfer parameters to another computer, click **Export** to write a file on the first device, and **Import** to read the file on the second device. The software will merge the imported parameters into the existing settings file.

## 3.2 Mobile Survey

To use the SpecFIDLER for mobile survey, carry the unit by the top handle, keeping the detector a uniform distance from the ground. Retract the legs if more convenient.

**NOTE:** Never set the detector face down on the ground without the tripod legs extended. The beryllium window will be damaged.

Use the **Rate** tab (Figure 12) to acquire data. The main plot displays the count rate versus time in black, along with the alarm threshold in blue. Time 0 indicates when the measurement started. Spikes in the count rate indicate potential hotspots that may warrant further sampling.




Figure 12. Rate tab.

The **Device** drop-down near the top left indicates the present detector. Typically, only one detector is connected to the tablet, so only one serial number appears in the drop-down list. The **SIMULATOR** option uses simulated data for training purposes, and the **(none)** option disconnects from all detectors. Changing the selection may take a few seconds due to the high voltage needing to be ramped up or down. If a message appears regarding a voltage not being specified, refer to Section 4.1 to perform a voltage calibration.

To connect to a different detector, first set the **Device** to **(none)**. Unplug the old detector from the tablet and plug in the new detector. Click **Scan** to refresh the list of detectors, then select the new detector from the **Device** drop-down.

The **Status** text box displays the present connection state:

- **BUSY**: Scanning for devices or ramping high voltage.
- **INACTIVE**: No detector connected.
- **READY**: Detector connected but not acquiring data.
- **RUNNING**: Detector acquiring data.
- **CLOSING**: Shutting down software.
- **ERROR**: A communication error occurred. Try connecting to the detector again.

The **Run time** drop-down specifies the total run time in seconds. Type in a value or choose an option from the list.

Click **Start** to begin the data acquisition and **Stop** to end the data acquisition before the total run time has elapsed. Click **Start** again to accumulate additional data. Note that the total run time may need to be increased to continue. Click **Clear** to discard accumulated data.

The **Int time** drop-down specifies the integration time. For example, a value of 3 means that the count rate is computed over the previous three seconds, while still updating every second. The plot is regenerated when the integration time changes. The integration time only affects the plot and not the exported files or streamed data.

The **Windowed** and **Calibrated** checkboxes control the count rate displayed in the plot, along with the associated alarm threshold. Clear **Windowed** to integrate the gross counts across the entire spectrum. The alarm threshold is set by the **Gross counts** controls in the **Settings** tab. Select **Windowed** but clear **Calibrated** to integrate the spectrum between two channels. Finally, if the energy calibration is valid, select both **Windowed** and **Calibrated** to integrate the spectrum between two energies in keV. The window bounds and alarm threshold are set by the appropriate **Rate window** controls in the **Settings** tab.

Use the scroll bar at the bottom of the plot to navigate through the data. The **Lock** checkbox prevents the graph from scrolling when new samples are added. Use the **Rate x-axis** field in the **Settings** tab to control the amount of data shown. A value of zero auto-scales the x axis.

Below the plot, the **Start date and time** indicates when the data acquisition initially began. The **Latitude** and **Longitude** provide the present GPS location. The **Rate** shows the present count rate after applying the selected integration time and windowing technique. The **Alarm** text box indicates the present alarm threshold. Finally, the three toggle buttons to the right control the audible alerts. If **Alarms** or **Clicks** is selected, the software plays a sound whenever the count rate exceeds the alarm threshold.

Returning to the toolbar, click **Import** to read a previous data file in CSV format. The present detector is disconnected and data acquisition disabled. After viewing data, click **Clear** and change back to the desired **Device**.

Click **Export** to write a data file in CSV format. The file contains one row for each second of data. Each row specifies the sample number, UNIX timestamp, real time in microseconds, GPS location, count rates, and 4096-channel spectrum. The first channel of the spectrum is the live time in microseconds. The UNIX timestamp corresponds to the end of the one-second sample. By default, the file is saved to a subfolder of the working directory (**c:\fidler** by default). The file can be loaded into AVID for processing.

Use the **Auto save** check box to automatically write a data file in CSV format when acquisition stops. The file name contains the device serial number as well as the start date and time.

In summary, field teams should perform the following steps for mobile survey:

- Select the correct **Device**.
- Check **Auto save**.
- Change the **Run time** to 3600 seconds and click **Start**.
- Press **Clicks** on the bottom right.
- Carry the detector around and listen for alarms. Adjust the alarm threshold as needed.
- Use the **Windowed** and **Int time** features for greater sensitivity, if needed.
- Make note of any hotspots for subsequent sampling.

### 3.3 Streaming to AVID

As an alternative to viewing data within the SpecFIDLER software, field teams may stream data to AVID for visualization and processing. This feature requires AVID 2022 Update 1 or later.

To enable streaming, check the box beside **Stream to AVID** in the **Settings** tab. Open AVID and configure the SpecFIDLER stream manager to connect to the SpecFIDLER software. Provide the IP address where the software is running (usually the local address 127.0.0.1) and the port number (4002 by default). The port number is defined in the settings file, as explained in Appendix B.

The SpecFIDLER software then transmits samples of data each second while acquisition is running. The data includes the UNIX timestamp, GPS location, count rates, 4096-channel spectrum, and energy calibration. The timestamp corresponds to the beginning of the sample.

### 3.4 Stationary Sampling

To use the SpecFIDLER for stationary sampling, extend the legs and place the unit over the desired location. The detector should be 0.3 m from ground level with the legs extended. The first measurement should be a representative background that matches the terrain type as closely as possible. Subsequent measurements can then use that background to determine the amount of contamination. However, analysis can be performed without a background if needed.

Use the **Spectra** tab (Figure 13) to acquire data. The plot superimposes the accumulated foreground in black and the present background in red. Most plutonium isotopes have one peak around 17 keV, whereas Am-241 has peaks at 17 and 60 keV.




Figure 13. Spectra tab.

The **Rate** and **Spectra** tabs display the same data and share many of the same controls. As a reminder, select the **Device** and check the **Status**. Enter the desired **Run time**, then use **Start** and **Stop** to control the data acquisition. **Clear** the accumulated data to start over.

The **Log scale** checkbox places the y-axis on a logarithmic scale. The **Calibrated** checkbox controls whether the x-axis has units of channels or energy in keV. Use the **Spectrum x-axis** fields in the **Settings** tab to adjust the bounds of the x-axis in either case. For example, the plot above shows the first 1024 out of 4096 channels.

Below the plot, the **Start date and time** indicates when the data acquisition initially began. The **Bkg date and time** identifies the corresponding background. The **Real time**, **Live time**, and **Counts** display the accumulated statistics. Finally, the **User**, **Site**, and **Comment** are saved in the N42.42 file.

Returning to the toolbar, click **Import** to read a previous data file in N42.42 format. The present detector is disconnected and data acquisition disabled. This action also replaces the background and detector calibrations with the values read from the file. After viewing data, click **Clear** and change back to the desired **Device**. This action reloads the default background and detector calibrations from the settings.

Click **Export** to write a data file in N42.42 format. The file contains the start date and time along with the accumulated real time, live time, and spectrum. The present background and detector calibrations are included as well. Unlike the CSV files generated from the **Rate** tab, only the final accumulated spectrum is saved; thus, the time series is not displayed on import.

Use the **Auto save** check box to automatically write a data file in N42.42 format when acquisition stops. As before, the file name contains the device serial number as well as the start date and time.

Click **Get bkg** to load the default background from the settings. The background is taken from the **Backgrounds** table in the **Settings** tab. The software selects the row that has **Enable** checked, matches the **Device**, and has the latest **Start date and time**. In addition to the background, the **User** and **Site** are taken from the **Default user** and **Default site** at the top of the view.

Click **Set bkg** to store the background in the settings as the new default for the device. The **Default user** and **Default site** are set as well. Older backgrounds may be disabled or removed in the **Settings** tab using the  button, if desired.

In summary, field teams should perform the following steps for stationary sampling:

- Position the detector above the background location.
- Select the correct **Device**.
- Check **Auto save**.
- Change the **Run time** to 300 seconds and click **Start**.
- Edit the **User**, **Site**, and **Comment** to describe the location.
- Click **Set bkg** to set the default background for subsequent data acquisitions.
- Position the detector above the first hotspot.
- Edit the **Comment** to describe the location.
- Check **Auto save**. Click **Clear** and **Start**.
- Repeat for subsequent hotspots.

### 3.5 Source Term

Use the **Source term** tab (Figure 14) to define the mixture used for analysis. The software can take a previous source term and apply decay corrections to create a new source term. The two tables display the nuclides, mass fractions, and activity fractions of each constituent in the mixture, before and after aging. Consult with an assessment scientist to determine which source term to use for the event at hand.

Click **Load** to bring in one of the **Available source terms** from the settings. The software populates the **INITIAL** table with the constituent nuclides, mass fractions, and activity fractions. The **Name** is also changed to deconflict from the original source term in the settings. If desired, rename the source term to be more descriptive.




Figure 14. Source term tab.

In the left panel, click **Add** to append a new row to the **INITIAL** table, and **Remove** to delete the highlighted row. Select the appropriate **Nuclide** in the first column and provide either the mass fraction or the activity fraction. The two radio buttons select which fraction is used for the decay corrections; the software calculates the other value automatically. Finally, enter the **Age** in years. Keep the **Age** at zero if no decay corrections are necessary.

Now click **Calculate**. The software populates the **CORRECTED** table with the decay-corrected nuclides, mass fractions, and activity fractions. The **Cal date and time** is also updated. This source term is the one used for the nuclide analysis.

Click **Get term** to load the source term from the settings. The source term is taken from the respective table in the **Settings** tab. The software selects the row that has **Enable** checked and has the latest **Cal date and time**.

Click **Set term** to store the source term in the settings. Subsequent runs of the software then load this source term by default.

**NOTE:** The new source term overwrites any existing source term with the same **Name**. However, the built-in source terms normally cannot be modified.

In summary, field teams and/or associated scientists should perform the following steps to define the source term in support of nuclide analysis:

- Ask an assessment scientist which initial source term and age to use, if necessary.
- Select the initial source term under **Available source terms** and click **Load**.
- Edit the **Name** and **Age** as needed.
- Click **Calculate**.
- Click **Set term** to set the default source term for subsequent analysis.

## 3.6 Nuclide Analysis

After collecting a stationary sample, use the **Analysis** tab (Figure 15) to compute the nuclide concentrations. The main plot displays the foreground spectrum in black, the background spectrum in red, and each region of interest (ROI) in blue. The background regions adjacent to each ROI are highlighted in red as well. The controls in the left panel specify various input parameters for the nuclide analysis. The tables at the bottom display the computed results.




Figure 15. Analysis tab.

The **Device** and **Status** on the top left reflect the detector state in the **Rate** and **Spectra** tabs. Below the plot, the **Start date and time** indicates when the data acquisition initially began, and the **Real time**, **Live time**, and **Counts** display the accumulated statistics.

On the left side, the **Source type and units** specifies whether the analysis is performed for a distributed source or a point source, and in units of  $\mu\text{Ci}$  or  $\text{Bq}$ . The point source option may be useful when analyzing a small sample (for example, a hot particle) underneath the detector.

The **Background algorithm** defines how the nuclide analysis computes the background. Select **One-window** to use a background measurement collected previously. Select **Three-window** to extrapolate the background counts from the background regions to the left and right of the ROI. The **One-window** method is generally more accurate, but the **Three-window** method may be useful if a representative background is not available.

The **Analysis algorithm** determines how the quantities in each ROI are linked. Select **Individual ROI** to compute the results for each ROI independently. The activity fractions from the specified source term are used to scale the total quantity. Select **Linked ROI** to propagate results from one ROI to another. Specifically, the quantity of Am-241 is calculated first using the net counts in the 60 keV ROI. The activity fractions are then adjusted for the 17 keV ROI to provide a consistent quantity of Am-241. The concentrations of the remaining nuclides are then calculated in the original manner. The **Linked ROI** option is useful when Am-241 is present but the fractional quantity is not known.

The **Height** should match the actual detector height. Recall that the default height with the legs extended is 0.3 meters.

Returning to the toolbar, click **Calculate** to run the nuclide analysis. The results are displayed in the two tables at the bottom. The **OVERALL** table provides the count rates and computed quantities for each ROI. The **SELECTED ROI** table lists the activity fraction, sensitivity parameters, and individual quantity for each nuclide in the source term. Select a different row in the **OVERALL** table to display the values for each ROI. In general, select the **60 keV** results if using Am-241 as a marker isotope, as these results are less affected by surface roughness and other uncertainties. Otherwise, select the **17 keV** results.

Make note of the quantities displayed in the **OVERALL** table. The **Overall** column provides the total quantity of all nuclides in the source term. The **Alpha** column provides the total quantity of all alpha emitters in the source term. This value excludes Pu-241 and other beta emitters. Finally, the **Am-241** column provides the quantity of just Am-241. The individual quantities for other nuclides are listed in the last column of the **SELECTED ROI** table.

Depending on the **Source type and units**, the quantities may be reported as activities (such as  $\mu\text{Ci}$ ) or areal concentrations (such as  $\mu\text{Ci}/\text{m}^2$ ). The column headers in the two tables update to match the desired value. If a quantity is less than the minimum detectable activity (MDA), the text **< MDA** will appear instead.

The **SELECTED ROI** table provides more information about the factors that went into the calculation. The **Yield** specifies the gamma emissions in the ROI per decay. The **Solid angle** is computed for gamma emissions directly underneath the detector. The **Transmission** factor accounts for the air attenuation between the ground and the detector. For distributed sources,

this factor also integrates the activity over an infinite disc, accounting for changes to the solid angle and path length. Finally, the **Int efficiency** gives the calibrated intrinsic efficiency.

Returning to the toolbar once again, the **Log scale** checkbox in the toolbar places the y-axis of the plot on a logarithmic scale, as before.

Click **Import** to read a previous data file in N42.42 format. Like the corresponding button on the **Spectrum** tab, the present detector is disconnected, data acquisition is disabled, and the background and detector calibrations are replaced. In addition, the software reads the input parameters and calculated results from the data file, if present.

**NOTE:** The source term is not saved to the data file. The calculated results will be different if the source term changed.

Click **Export** to write the data and analysis results to a file in N42.42 format. The analysis results are written to the file in the same units as the calculations. Use the **Auto save** check box to automatically perform the analysis and export the results.

In summary, field teams and/or associated scientists should perform the following steps for nuclide analysis:

- Check **Auto save**.
- Select **Linked ROI** if Am-241 is present but the fractional quantity is not known. Otherwise, select **Individual ROI**.
- Unless examining a point source, use **Distributed ( $\mu\text{Ci}/\text{m}^2$ )** for **Source type and units**.
- Click **Calculate**.
- Select the **60 keV** row in the **OVERALL** table if using Am-241 as a marker isotope (which implies that the fractional quantity is known). Otherwise, select the **17 keV** row.
- Record the **Overall**, **Alpha**, and **Am-241** concentrations from that row.

### 3.7 Batch Analysis

Use the **Batch** tab (Figure 16) to reprocess historical data. The table in the center lists the file names being processed, the associated input parameters for the nuclide analysis, and a summary of the computed results. The controls at the bottom display the full results for the selected row.

Click **Import** to read data files in N42.42 format. A window appears to select a **Parent directory**. The table is populated with all files with an .n42 extension in that directory, along with any subdirectories. Files that were exported from the **Energy cal** or **Efficiency cal** tabs are excluded so the calibration information is not lost. The software displays a message indicating the number of files read and skipped.

Click **Add** to append additional rows to the table. A window appears to select one or more files. As before, calibration files are skipped. Click **Remove** to delete the selected rows from the table.




Figure 16. Batch tab.

Use the controls below the toolbar to specify which modifications to apply to the nuclide analysis. Choose a **Source term** and optionally a new **Source type and units**, **Background algorithm**, and **Analysis algorithm**.

Select one or more rows in the table or click **Select all**. Finally, click **Calculate** to update the results for the selected rows.

After performing any desired updates, click **Export** to write the data and analysis results. A window appears to select a new **Parent directory**. The data files are saved to this directory using the same relative paths and filenames.

**NOTE:** Exporting to the old **Parent directory** overwrites the data files.

The **Report** button writes a summary of the computed results in CSV format. The file contains one row for each data file. Each row specifies the device, user, site, comment, GPS location, start date and time, real time, live time, and quantities for each ROI using the selected units.

### 3.8 Shutdown

When data acquisition and analysis is complete, click **Shutdown** in the **Settings** tab to shut down the SpecFIDLER and return to the DFM software. Alternatively, close the window using the **X** in the upper right corner. The shutdown process takes a few seconds to ramp down the bias voltage and disconnect from the usbBase.

**NOTE:** Do not unplug the tablet from the detector until the usbBase is disconnected. This may be done by shutting down the software or by changing the **Device** to **(none)**.

## 4.0 Calibration

The SpecFIDLER requires several calibration steps before use: a voltage calibration performed when commissioning a detector, an energy calibration performed daily, and an efficiency calibration performed daily. The remainder of this section details the calibration procedures.

### 4.1 Voltage Calibration

The voltage calibration establishes the bias voltage for the detector. The detector must have a voltage listed in the **Settings** tab; otherwise, data acquisition will be disabled. The voltage calibration should only need to be performed when commissioning a new detector unless the performance changes significantly over time.

An Am-241 source is necessary to perform the voltage calibration. The goal is to have the spectrum meet two requirements (Figure 17). First, the 13 keV x-ray should be visible as a shoulder to the 17 keV peak. Second, and more importantly, the 60 keV peak should return to background prior to channel 250.




Figure 17. Am-241 spectrum with good high voltage setting.

Field teams or maintenance personnel should perform the following steps for voltage calibration:

- Place the Am-241 source on the ground directly underneath the detector.
- Go to the **Settings** tab and click the **+** button next to **Voltages**.
- Set **Volts** to 1000 and ensure that **Enabled** is checked.
- On the **Spectrum** tab, change the **Run time** to 300 or 600 seconds and click **Start**.
- Adjust the voltage up or down as needed.
- After each change, change the **Device** to **DISCONNECTED** and then to the original serial number. This action applies the new bias voltage to the detector.

**NOTE:** Setting the bias voltage above 1200 V is not recommended. Do not exceed 1500 V or the detector may be damaged.

## 4.2 Energy Calibration

The energy calibration translates a channel number to the corresponding energy in keV. These conversion factors are created by presenting a source to the instrument, acquiring a spectrum, and selecting the proper peak. It is recommended to perform the energy calibration daily prior to deployment. Although the software supports different sources, the energy calibration can be completed using Am-241 alone. Thus, the following discussion uses Am-241 for illustration.

Use the **Energy Cal** tab (Figure 18) to perform the energy calibration. The main plot displays the foreground spectrum in black, the fitted peaks in red, and each region of interest (ROI) in blue. The table of peaks appears to the left, and the computed calibration coefficients on the bottom.

The **Device** and **Status** indicate the present detector and connection status. Use the **Spectrum** tab to select the detector and control data acquisition. The live spectrum is also visible in the **Energy cal** tab if **Show foreground** is checked.

Once the live spectrum has smooth peaks, click **Add** to append a new row to the table. This action makes a reference copy of the live spectrum. Thus, one can restart the data acquisition with a different calibration source and add another peak, if needed. Select a row in the table to display the associated reference spectrum. Click **Remove** to delete unneeded entries.

For each row, select the **Peak** in the first column and click on the corresponding peak in the plot. The **Channel** is computed automatically. If necessary, adjust the **Fit range** to achieve a good fit. Alternatively, manually input the desired **Channel**.

Click **Calculate** to compute the calibration coefficients. This action updates the **Cal date and time** at the top, along with the **Intercept**, **Slope**, and **Quadratic** terms at the bottom. For a two-point calibration, the **Quadratic** term will be zero. The software performs various checks to ensure the calibration makes sense and displays a warning message if something appears wrong.

The **Log scale** checkbox places the y-axis on a logarithmic scale.




Figure 18. Energy Cal tab.

The **Import** and **Export** buttons read and write data files in N42.42 format. The data files exported by the **Energy cal** tab contain all the reference spectra in addition to the foreground spectrum.

Click **Get cal** to load the default energy calibration from the settings. The calibration is taken from the **Energy cal** table in the **Settings** tab. The software selects the row that has **Enable** checked, matches the **Device**, and has the latest **Cal date and time**.

Click **Set cal** to store the energy calibration in the settings as the new default for the device. Older energy calibrations may be disabled in the **Settings** tab by clearing the **Enable** checkbox, or removed completely using the **-** button, if desired.

In summary, field teams should use the following procedure for energy calibration:

- Position the detector at a known background location.
- Place the Am-241 source on the ground directly underneath the detector.
- On the **Spectrum** tab, change the **Run time** to 300 seconds and click **Start**.
- On the **Energy cal** tab, click **Add** two times once data acquisition is complete.

- Change the **Peak** columns to **Am-241: 15.7** and **Am-241: 59.5**.
- Select each row and click the corresponding peaks in the plot.
- Click **Calculate** to compute the energy calibration.
- Click **Export** to save the energy calibration to an N42.42 file.
- Click **Set cal** to store the energy calibration in the settings.

### 4.3 Efficiency Calibration

The efficiency calibration determines the intrinsic efficiency of the detector for each ROI. Like the energy calibration, it is recommended to perform the efficiency calibration daily prior to deployment. Although the software supports different sources, typically just Am-241 is used. An activity of 2  $\mu$ Ci is recommended.

Use the **Efficiency Cal** tab (Figure 19) to perform the efficiency calibration. The main plot displays the foreground spectrum in black, the background spectrum in red, each ROI in blue, and each background region in red. The input parameters for the calibration appear to the left, and the table of computed efficiencies on the bottom.




Figure 19. Efficiency Cal tab.

As before, the **Device** and **Status** indicate the present detector and connection status. Use the **Spectrum** tab to select the detector and control data acquisition.

On the left side, specify the **Nuclide** used for the efficiency calibration, the **Age** in years, and the **Initial** activity in microcuries. The software automatically computes the **Corrected** activity. Also specify the **Plastic** thickness on top of the source, in millimeters, if using a non-electroplated source, along with the actual **Height** of the detector.

Returning to the toolbar, click **Calculate** to perform the efficiency calibration. This action updates the **Cal date and time** at the top, along with table of results at the bottom. As with the energy calibration, the software performs various checks to ensure the calibration makes sense and displays a warning message if something appears wrong.

One row appears in the table for each ROI and background method (one-window and three-window). The count rates, sensitivity factors, and computed intrinsic efficiency are all listed. As with the nuclide analysis, the **Yield** specifies the gamma emissions in the ROI per decay. The **Solid angle** is computed for gamma emissions directly underneath the detector. The **Transmission** factor accounts for the air attenuation between the ground and the detector.

The **Log scale** checkbox places the y-axis on a logarithmic scale, as before.

The **Import** and **Export** buttons read and write data files in N42.42 format. The data files exported by the **Efficiency cal** tab contain additional information about the efficiency calibration as remarks.

Click **Get cal** to load the default efficiency calibration from the settings. The calibration is taken from the **Efficiency cals** table in the **Settings** tab. The software selects the row that has **Enable** checked, matches the **Device**, and has the latest **Cal date and time**.

Click **Set cal** to store the efficiency calibration in the settings as the new default for the device. Older efficiency calibrations may be disabled in the **Settings** tab by clearing the **Enable** checkbox, or removed completely using the  button, if desired.

In summary, field teams should use the following procedure for efficiency calibration:

- Collect the background as described in Section 3.4.
- Perform the energy calibration as described in Section 4.2.
- Keep the same Am-241 spectrum from the energy calibration.
- On the **Efficiency cal** tab, set the **Nuclide** to **Am-241**.
- Also specify the **Age**, **Initial** activity, **Plastic** thickness, and detector **Height**.
- Change the **Peak** columns to **Am-241: 15.7** and **Am-241: 59.5**.
- Click **Calculate** to compute the efficiency calibration.
- Click **Export** to save the energy calibration to an N42.42 file.
- Click **Set cal** to store the efficiency calibration in the settings.

## 5.0 Maintenance

This section discusses common maintenance tasks for the SpecFIDLER and gives suggestions for troubleshooting.

### 5.1 Version Information

Click **About** in the **Settings** tab to display the software version and other information.

### 5.2 Upgrading from Previous Versions

The SpecFIDLER software is not completely compatible with the settings used for older versions. In general, the software will read most parameters from the old settings file; however, some calibration steps need to be repeated. Use the following procedure when upgrading:

1. When opening the software, a warning message appears that about the settings format having the incorrect format. Dismiss this message as it is expected.
2. Go to the **Settings** tab and confirm that the **Voltages** appear correct.
3. If upgrading from version 1, delete all **Efficiency cals** from the **Settings** tab. Older versions of the software used a different method to perform the efficiency calibration. Thus, these calibrations are invalid and will show as blank.
4. Click **Save** to save the settings file in the updated format.

One can also manually specify all parameters in the **Settings** tab, including the **Backgrounds**, **Energy cals**, and **Efficiency cals**. However, it is usually easier to simply repeat the calibrations.

### 5.3 Replacing usbBase

Occasionally a usbBase will stop communicating with the SpecFIDLER software. The cause of this issue is unknown, but it seems to occur most frequently when first commissioning a detector. Use the following procedure to exchange a base:

1. Unplug the old base from the USB hub.
2. Carefully cut the plastic heat shrink between the old base and the detector.
3. Unplug the old base from the detector.
4. Plug the new base onto the detector, taking care to line up the key on the detector end with the notch on the base socket.
5. Replace the heat shrink. The outer diameter of the usbBase is about 2.25".
6. Perform a voltage calibration, energy calibration, and efficiency calibration on the new base.

## 5.4 Log Files

The SpecFIDLER software saves daily log files to the SpecFIDLER working directory (**c:\fidler** by default). These log files contain more detailed information about warnings and errors encountered by the software.

## 6.0 Algorithms

This section describes the algorithms used for background subtraction, energy calibration, efficiency calibration, and nuclide analysis. These algorithms incorporate the simplified calibration procedure developed by the Remote Sensing Laboratory (RSL) [1]. In addition, the calculation framework draws heavily from the spreadsheet developed at Sandia National Laboratories (SNL) [2].

### 6.1 Background Subtraction

The one-window method uses a prior background measurement to compute the net count rate in counts per minute (cpm):

1. Integrate the counts in the foreground spectrum between the ROI energy limits, interpolating between channels. Divide by the live time to compute the total count rate  $C$ .
2. Repeat the above for the background spectrum to compute the background count rate  $B$ .
3. Subtract  $C - B$  to compute the net count rate  $N$ .

In contrast, the three-window method extrapolates the background counts from adjacent regions in the spectrum:

1. Integrate the counts in the foreground spectrum between the ROI energy limits, interpolating between channels. Divide by the live time to compute the total count rate  $C$ .
2. Repeat the above for the left and right windows adjacent to the ROI to compute the count rates  $L$  and  $R$ .
3. Use the following formula to compute the net count rate:

$$N = C - \frac{1}{2} \left( \frac{L}{\Delta E_L} + \frac{R}{\Delta E_R} \right) \Delta E_C$$

where  $\Delta E_L$ ,  $\Delta E_R$ , and  $\Delta E_C$  denote the energy span of each window (keV).

### 6.2 Energy Calibration

Clicking on a peak in the **Energy Cal** tab causes the software to fit the peak to a Gaussian function and report the center channel. This process involves the following steps:

1. Find the local maximum near the click. The search distance is specified by the **Fit range**.
2. Find the local minima on either side using the same search distance.
3. Find the points halfway in amplitude between the minima and maximum.
4. Use a truncated-Newton optimization algorithm to minimize the mean squared error between the spectrum and the Gaussian function

$$a \exp\left(-\frac{(i - \mu)^2}{2\sigma^2}\right) + b$$

between the two half maximum points. The value  $b$  specifies a constant baseline underneath the peak, which should be accurate enough for the present purpose.

5. Record the center channel  $\mu$ .

To calculate the coefficients of the energy calibration, the software performs a quadratic fit between the channel numbers and associated peak energies. If only two peaks are specified, a linear fit is used instead.

The software then checks the results to ensure that the slope of the energy calibration remains positive and varies by less than 10% across the ROI range. In addition, the software verifies that the regression matches the actual peak energies to within 5%. Any unusual findings cause the software to display a warning message.

### 6.3 Efficiency Calibration

To compute the intrinsic efficiency  $\varepsilon$  of each ROI, the software uses the following formula:

$$\varepsilon = \frac{N}{k Q Y S T}$$

Here  $N$  is the net count rate in the ROI (cpm),  $k$  is a unit conversion factor (dpm/ $\mu$ Ci),  $Q$  is the decay-corrected source activity ( $\mu$ Ci),  $Y$  is the yield of the nuclide in the ROI,  $S$  is the solid angle fraction for a point source directly underneath the detector, and  $T$  is the transmission factor through the intervening plastic and air.

It is assumed that the detector has the same intrinsic efficiency to all gamma emissions in the ROI. As the width of the ROI is relatively small, and the low-energy gamma emissions from transuranic nuclides are consistent, this assumption should not introduce significant error.

The solid angle fraction  $S$  is the ratio of the detector area to the surface area of a sphere with radius  $h$ :

$$S = \frac{R^2}{4h^2}$$

where  $R$  is the detector radius (m).

The transmission factor  $T$  is the product of two terms:

$$T = \exp(-\mu_p d) \exp(-\mu_a h)$$

where  $\mu_p$  is the linear attenuation coefficient of the plastic (1/m),  $d$  is the plastic thickness (m),  $\mu_a$  is the linear attenuation coefficient of the air (1/m), and  $h$  is the detector height (m). Both attenuation coefficients are taken at the mean energy of the ROI with representative densities.

For greater accuracy, the mean path lengths should be used in place of the plastic thickness and height; these values are about 10% larger than the straight-line distances given a detector height of 0.30 m. In practice, other sources of error will dominate.

## 6.4 Nuclide Analysis

Given a source term with a mixture of nuclides, the software first calculates the overall quantity  $Q$  in each ROI:

$$Q = \frac{N}{\sum_i (F_i Y_i) S T \varepsilon k}$$

Here  $N$  is the net count rate in the ROI (cpm),  $F_i$  is the activity fraction for one nuclide,  $Y_i$  is the yield of that nuclide in the ROI,  $S$  is the solid angle fraction for a point source directly underneath the detector,  $T$  is the transmission factor through the air,  $\varepsilon$  is the intrinsic efficiency in the ROI, and  $k$  is a unit conversion factor. This formulation supports both point sources and distributed sources.

The activity fractions are computed from the mass fractions specified by the source term, and then scaled to sum to one:

$$\sum_i F_i = 1$$

As before, the solid angle fraction  $S$  is the ratio of the detector area to the surface area of a sphere with radius  $h$ :

$$S = \frac{R^2}{4h^2}$$

where  $R$  is the detector radius (m).

For a point source, the transmission factor  $T$  is simply

$$T = \exp(-\mu_a h)$$

where  $\mu_a$  is the linear attenuation coefficient of the air (1/m) and  $h$  is the detector height (m). For a distributed source, the transmission factor integrates activity from differential area  $dA$  over infinite disc  $D$ , accounting for changes to the solid angle and path length:

$$T = \iint_D \frac{h^2}{h^2 + r^2} \cos \varphi \exp\left(-\mu_a \sqrt{h^2 + r^2}\right) dA$$

Here  $r$  is the radial offset to  $dA$ , whereas  $\varphi$  represents the angle between the vertical line through the detector center and the line from the detector center to  $dA$ . The first term accounts for the decrease in solid angle as  $dA$  moves further away from the detector. The second term accounts for the decrease in geometric efficiency as emissions from  $dA$  intercept the detector at an angle. The final term specifies the air attenuation over the path.

The corresponding integral

$$T = \int_0^{2\pi} \int_0^\infty \frac{h^3}{(h^2 + r^2)^{3/2}} \exp(-\mu_a \sqrt{h^2 + r^2}) r dr d\theta$$

has the solution

$$T = 2\pi h^2 (\exp(-\mu_a h) + \mu_a h \operatorname{Ei}(-\mu_a h))$$

where  $\operatorname{Ei}$  represents the exponential integral.

The unit conversion factor  $k$  depends on the selected **Source type and units**. For a point source, the result  $Q$  will be in  $\mu\text{Ci}$ ,  $\text{Bq}$ , or  $\text{kBq}$ . For a distributed source,  $Q$  will be in  $\mu\text{Ci}/\text{m}^2$  or  $\text{Bq}/\text{m}^2$ .

The software also calculates the overall MDA in each ROI:

$$MDA = \frac{2.71 + 4.66\sqrt{B}}{\sum_i (F_i Y_i) T S \varepsilon k \sqrt{t}}$$

Here  $B$  is the background count rate in the ROI (cpm),  $t$  is the live time, and all other terms are the same as before.

The quantity and MDA of an individual nuclide are equal to the overall values multiplied by the activity fraction  $F_i$ . The software highlights the computed quantity of Am-241 as well as the sum of all alpha emitters.

If the ROI computations are performed independently, the results may be different for each ROI. One source of uncertainty is the relative abundance of Am-241 versus other isotopes. The “independent” method assumes that the specified activity fractions are fixed. However, the quantity of Am-241 can be deduced from the 60 keV ROI and then propagated to the 17 keV ROI. The “linked” method implements this approach. The calculations proceed as above, but the 17 keV results are then adjusted as follows:

1. Copy the quantity  $Q_i$  of Am-241 from the 60 keV ROI to the 17 keV ROI.
2. Scale the activity fraction  $F_i$  for Am-241 to obtain the desired value of  $Q_i$ .
3. Scale  $F_i$  for all other isotopes so that  $\sum_i (F_i Y_i)$  is the same as before. This returns the overall quantity  $Q$  in the 17 keV ROI to its original calculated value. This step assumes that the source term defines other isotopes besides Am-241.
4. After the above steps,  $\sum_i F_i \neq 1$ . Thus, scale  $Q$  and all  $F_i$  so that  $\sum_i F_i = 1$  once more.

Note that the 17 keV ROI will specify the new activity fractions, but the 60 keV ROI will still contain the original ones.

## 7.0 References

- [1] C Okada, "The SpecFIDLER", Dec. 2018.
- [2] M Enghauser, "SNL\_SpecFIDLER\_V000", Excel spreadsheet, Nov. 2019.
- [3] TurboFRMAC Radionuclide Viewer, version 12.0.0, Mar. 2024.
- [4] NuDat 3.0, <https://www.nndc.bnl.gov/nudat3/>
- [5] Live Chart of Nuclides, <https://www-nds.iaea.org/relnsd/vcharthtml/VChartHTML.html>
- [6] U.S. Department of Energy, "Good practices for occupational radiological protection in plutonium facilities", DOE STD-1128-2013, Jan. 2020.
- [7] J Clow *et al*, "Specific activities and DOE-STD-1027-92 Hazard Category 2 thresholds", Los Alamos National Laboratory, LA-12846-MS, Nov. 1994.

## Appendix A – Configuration File

The SpecFIDLER software uses the file **SpecFidler.exe.config** to configure general application settings. This file is in the same directory as the application **SpecFidler.exe**.

The **log4net** section configures event logging. The software records important messages to a log file (**C:\fidler\SpecFIDLER.log** by default) for debugging purposes. The **file** key specifies the filename. Use the log file to diagnose any problems when manually editing the settings file.

The **appSettings** section configures various other settings. If **NoDefaults** is **true**, the software will not load the default user settings on startup. Further details are in Appendix B. The **WorkingDir** defines the working directory for data files (**C:\fidler** by default). Finally, if **Simulated** is **true**, the software provides the option for simulated detector data.

An example configuration file appears below.

```

<?xml version="1.0" encoding="utf-8"?>
<configuration>
  <configSections>
    <section name="log4net"
      type="log4net.Config.Log4NetConfigurationSectionHandler, log4net"/>
  </configSections>
  <log4net>
    <root>
      <level value="INFO"/>
      <appender-ref ref="RollingFileAppender"/>
    </root>
    <appender name="RollingFileAppender"
      type="log4net.Appender.RollingFileAppender">
      <appendToFile value="true"/>
      <file value="C:\fidler\SpecFIDLER.log"/>
      <layout type="log4net.Layout.PatternLayout">
        <conversionPattern value="%date{HH:mm:ss} %-5level %logger{1} -
          %message%newline%exception"/>
      </layout>
      <lockingModel type="log4net.Appender.FileAppender+MinimalLock"/>
      <maxSizeRollBackups value="10"/>
      <maximumFileSize value="100KB"/>
      <rollingStyle value="Size"/>
      <staticLogFileName value="true"/>
    </appender>
  </log4net>
  <appSettings>
    <add key="NoDefaults" value="false"/>
    <add key="WorkingDir" value="C:\fidler\"/>
    <add key="Simulated" value="true"/>
    <add key="ClientSettingsProvider.ServiceUri" value="" />
  </appSettings>
  (truncated)
</configuration>

```

## Appendix B – Settings File

The SpecFIDLER software uses another file named **settings.xml** to store all user settings, such as backgrounds, calibrations, and source terms. Also included are the nuclide library and regions of interest required for analysis. This file is stored in the directory defined by the **WorkingDir** application setting (**C:\fidler** by default) described in Appendix A. Some of the user settings may be modified through the software, but many cannot, either because they are used internally or locked against edits.

The software also has built-in default settings. Unless the **NoDefaults** application setting described in Appendix A is **true**, the default settings are loaded first on startup. The software then imports **settings.xml** if that file exists, or built-in example settings otherwise. Finally, users may import other settings files afterwards under the **Settings** tab. Both import operations employ the following general logic:

- If an equivalent value does not exist already, add it.
- Otherwise, if the existing value is not locked, replace it.

The nuclide library, peaks for energy calibration, regions of interest, selected source terms, and selected models for simulated mode are all locked in the built-in default settings. This mechanism allows newer versions of the software to specify updated physics parameters as needed. Advanced users who wish to evaluate different parameters should set **NoDefaults** to **true** prior to hand-editing **settings.xml**. To restore the software back to application defaults, simply delete **settings.xml** and set **NoDefaults** to **false**.

The remainder of this appendix provides an example settings file with annotations describing each section.

First are general preferences, such as the y-axis scale, user name, and so forth. These values are never locked and thus are replaced with the imported settings file.

```
<?xml version="1.0" encoding="utf-8" ?>
<SpecFIDLER>
  <audio>false</audio>
  <calibratedData>false</calibratedData>
  <fitRange>100</fitRange>
  <logarithmicScale>false</logarithmicScale>
  <site></site>
  <user>CMRT / FRMAC</user>
  <windowedSpectrum>false</windowedSpectrum>
```

The **alarmThresholds** section defines the count rate thresholds for the audible alarm. These values are never locked.

```
<alarmThresholds>
  <channelWindow>100</channelWindow>
  <energyWindow>100</energyWindow>
  <grossCounts>500</grossCounts>
</alarmThresholds>
```

The **backgrounds** section provides the background measurements for each device. Location information is saved with the background. These values are never locked.

```
<backgrounds>
  <background>
    <enabled>true</enabled>
    <deviceId>SIMULATOR</deviceId>
    <acquisitionDate>2000-01-01T00:00:00</acquisitionDate>
    <realTime>3598.480</realTime>
    <liveTime>3597.989</liveTime>
    <spectrum>1 1 2 3 4 7 12 27 50 92 171 300 374 (truncated) </spectrum>
    <latitude>46.349149028339191</latitude>
    <longitude>-119.27910736043991</longitude>
    <accuracy>1</accuracy>
  </background>
</backgrounds>
```

The **efficiencyCalibrations** section gives the efficiency calibrations for each device. One component exists for each ROI and background algorithm. The **intrinsicEfficiency** specifies counts per incident gamma in the ROI. These values are never locked.

```
<efficiencyCalibrations>
  <efficiencyCalibration>
    <enabled>true</enabled>
    <deviceId>SIMULATOR</deviceId>
    <calibrationDate>2015-09-09T00:00:00</calibrationDate>
    <efficiencyComponents>
      <efficiencyComponent>
        <region>17</region>
        <backgroundAlgorithm>OneWindow</backgroundAlgorithm>
        <intrinsicEfficiency>0.596370309</intrinsicEfficiency>
      </efficiencyComponent>
    </efficiencyComponents>
  </efficiencyCalibration>
</efficiencyCalibrations>
```

(truncated)

The **energyCalibrations** section gives the energy calibrations for each device. These values are never locked.

```
<energyCalibrations>
  <energyCalibration>
    <enabled>true</enabled>
    <deviceId>SIMULATOR</deviceId>
    <calibrationDate>2015-09-09T00:00:00</calibrationDate>
    <yIntercept>-0.13483146067415</yIntercept>
    <slope>0.308988764044944</slope>
    <quadratic>0</quadratic>
  </energyCalibration>
</energyCalibrations>
```

The **models** section provides the spectra used by the simulator. The spectrum must include 4096 values. All values except for the **enabled** flag are locked if specified.

```

<models>
  <model>
    <enabled>false</enabled>
    <locked>true</locked>
    <name>Background</name>
    <acquisitionDate>2000-01-01T00:00:00</acquisitionDate>
    <realTime>3598.480</realTime>
    <liveTime>3597.989</liveTime>
    <spectrum>1 1 2 3 4 7 12 27 50 92 171 300 374 (truncated) </spectrum>
  </model>
<(truncated)>
</models>

```

The **nuclides** section provides various parameters for nuclides of interest. The **key** is a unique identifier. The **halfLife** is in years, whereas the **specificActivity** is in Bq per gram. Both values are taken from the TurboFRMAC Radionuclide Viewer. The **yield** for each **emission** is taken from NuDat [4], with metastable states deconflicted using Livechart [5]. All values are locked if specified.

```

<nuclides>
  <nuclide>
    <locked>true</locked>
    <key>Am-241</key>
    <name>Am-241</name>
    <category>Am241</category>
    <single>true</single>
    <halfLife>4.3220000e+002</halfLife>
    <specificActivity>1.2700000e+011</specificActivity>
    <decayProduct>Np-237</decayProduct>
    <branchingRatio>1.00000e+000</branchingRatio>
    <emissions>
      <emission>
        <region>17</region>
        <yield>3.70000e-001</yield>
      </emission>
      <emission>
        <region>59.5</region>
        <yield>3.59180e-001</yield>
      </emission>
    </emissions>
  </nuclide>
<(truncated)>
</nuclides>

```

The **output** section enables auto saving and provides additional parameters for the output files, such as the instrument information given in the .n42 file. Note that the **instrumentClassCode** and **detectorCategoryCode** must have one of the enumerated values in the N42.42 schema. These values are never locked.

```
<output>
  <autoSaveRate>false</autoSaveRate>
  <autoSaveSpectrum>false</autoSaveSpectrum>
  <autoSaveAnalysis>false</autoSaveAnalysis>
  <instrumentManufacturerName> Pacific Northwest National Laboratory
  </instrumentManufacturerName>
  <instrumentModelName>Scintillation Crystal</instrumentModelName>
  <instrumentClassCode>Radionuclide Identifier</instrumentClassCode>
  <instrumentComponentName>SpecFIDLER Software</instrumentComponentName>
  <detectorCategoryCode>Gamma</detectorCategoryCode>
  <detectorKindCode>NaI</detectorKindCode>
</output>
```

The **peaks** section lists possible peaks for the energy calibration. The **energy** has units of keV. All values are locked if specified.

```
<peaks>
  <peak>
    <locked>true</locked>
    <source>Am-241</source>
    <energy>15.7</energy>
  </peak>
  <peak>
    <locked>true</locked>
    <source>Am-241</source>
    <energy>59.5</energy>
  </peak>
</peaks>
```

(truncated)

The **rateWindows** section provides the options for the rate chart time binning. These values are never locked.

```
<rateWindows selected="1">
  <seconds>1</seconds>
  <seconds>2</seconds>
  <seconds>3</seconds>
  <seconds>5</seconds>
  <seconds>10</seconds>
  <seconds>15</seconds>
  <seconds>30</seconds>
  <seconds>60</seconds>
</rateWindows>
```

The **regions** section lists the ROI for analysis. The **key** is a unique identifier. The **order** specifies the analysis order. The **energyLow** and **energyHigh** are the ROI bounds in keV. The **backgroundLow** and **backgroundHigh** define the background region in keV for the three-window method. The **airAttenuationCoefficient** gives the linear attenuation coefficient for air, in units of inverse meters. Finally, the **plasticAttenuationCoefficient** provides a similar value for the plastic on top of the calibration source. All values are locked if specified.

```

<regions>
  <region>
    <locked>true</locked>
    <key>17</key>
    <name>17 keV</name>
    <order>2</order>
    <energyLow>11.0</energyLow>
    <energyHigh>23.0</energyHigh>
    <backgroundLow>7.0</backgroundLow>
    <backgroundHigh>27.0</backgroundHigh>
    <airAttenuationCoefficient>1.2640e-01</airAttenuationCoefficient>
    <plasticAttenuationCoefficient>4.7021e+01
      </plasticAttenuationCoefficient>
  </region>
  <region>
    <locked>true</locked>
    <key>59.5</key>
    <name>60 keV</name>
    <order>1</order>
    <energyLow>54.0</energyLow>
    <energyHigh>66.0</energyHigh>
    <backgroundLow>50.0</backgroundLow>
    <backgroundHigh>70.0</backgroundHigh>
    <airAttenuationCoefficient>2.1003e-02</airAttenuationCoefficient>
    <plasticAttenuationCoefficient>8.6226e+00
      </plasticAttenuationCoefficient>
  </region>
</regions>

```

The **runTimes** section provides the options for the run time. These values are never locked.

```

<runTimes selected="600">
  <seconds>30</seconds>
  <seconds>60</seconds>
  <seconds>90</seconds>
  <seconds>180</seconds>
  <seconds>300</seconds>
  <seconds>600</seconds>
  <seconds>1200</seconds>
  <seconds>1800</seconds>
  <seconds>3600</seconds>
</runTimes>

```

The **sourceTerms** section lists the mixtures of nuclides defined for analysis. All values except for the **enabled** flag are locked if specified. The generic plutonium source terms are taken from Table 2.1 in [6]. The plutonium material type (MT) source terms are taken from Table 3b in [7].

```

<sourceTerms>
  <sourceTerm>
    <enabled>false</enabled>
    <locked>true</locked>
    <name>WeaponsGradePu</name>
    <calculationDate>2000-01-01T00:00:00</calculationDate>
    <constituents>
      <constituent>
        <nuclide>Pu-239</nuclide>
        <massFraction>9.36000e-001</massFraction>
      </constituent>
      <constituent>
        <nuclide>Pu-240</nuclide>
        <massFraction>6.00000e-002</massFraction>
      </constituent>
      <constituent>
        <nuclide>Pu-241</nuclide>
        <massFraction>4.00000e-003</massFraction>
      </constituent>
    </constituents>
  </sourceTerm>
</sourceTerms>

```

(truncated)

The **streaming** section specifies the local IP address and port number of the streaming server. Set the IP address to 0.0.0.0 to accept any incoming connections. These values are never locked.

```

<streaming>
  <enabled>false</enabled>
  <ipAddress>0.0.0.0</ipAddress>
  <portNumber>4002</portNumber>
</streaming>

```

The **voltages** section gives the high voltage setpoints for each device. These values are never locked.

```

<voltages>
  <voltage>
    <enabled>true</enabled>
    <deviceId>SIMULATOR</deviceId>
    <calibrationDate>2015-09-09T00:00:00</calibrationDate>
    <volts>1000</volts>
  </voltage>
</voltages>

```

The **window** section specifies the bounds for the rate window. The **channelLow** and **channelHigh** are used for uncalibrated spectra. The **energyLow** and **energyHigh** are used for the calibrated spectra. These values are never locked.

```
<window>
  <channelLow>0</channelLow>
  <channelHigh>256</channelHigh>
  <energyLow>11</energyLow>
  <energyHigh>66</energyHigh>
</window>
```

Finally, the **xAxis** section specifies the bounds for the x-axis on the plots. The **channelLow** and **channelHigh** are used for uncalibrated spectra. The **energyLow** and **energyHigh** are used for the calibrated spectra. These values are never locked.

```
<xAxis>
  <channelLow>0</channelLow>
  <channelHigh>1024</channelHigh>
  <energyLow>0</energyLow>
  <energyHigh>250</energyHigh>
</xAxis>
</SpecFIDLER>
```

## Appendix C – Licensing

The SpecFIDLER software uses the libftdi and libusb-win32 libraries, which are individually released under version 2.1 of the GNU Lesser General Public License. The text of this license is included in Section C.1 for reference. Please contact the authors if the relevant object and/or source code is desired to relink the software with modified versions of these libraries.

The SpecFIDLER software also uses the Ookii.Dialogs.Wpf library, which is released under the BSD 3-Clause “New” or “Revised” License. The text of this license is included in Section C.2.

### C.1 License for libftdi and libusb-win32 Libraries

GNU LESSER GENERAL PUBLIC LICENSE  
Version 2.1, February 1999

Copyright (C) 1991, 1999 Free Software Foundation, Inc.  
51 Franklin Street, Fifth Floor, Boston, MA 02110-1301 USA  
Everyone is permitted to copy and distribute verbatim copies  
of this license document, but changing it is not allowed.

[This is the first released version of the Lesser GPL. It also counts  
as the successor of the GNU Library Public License, version 2, hence  
the version number 2.1.]

#### Preamble

The licenses for most software are designed to take away your freedom to share and change it. By contrast, the GNU General Public Licenses are intended to guarantee your freedom to share and change free software--to make sure the software is free for all its users.

This license, the Lesser General Public License, applies to some specially designated software packages--typically libraries--of the Free Software Foundation and other authors who decide to use it. You can use it too, but we suggest you first think carefully about whether this license or the ordinary General Public License is the better strategy to use in any particular case, based on the explanations below.

When we speak of free software, we are referring to freedom of use, not price. Our General Public Licenses are designed to make sure that you have the freedom to distribute copies of free software (and charge for this service if you wish); that you receive source code or can get it if you want it; that you can change the software and use pieces of it in new free programs; and that you are informed that you can do these things.

To protect your rights, we need to make restrictions that forbid distributors to deny you these rights or to ask you to surrender these rights. These restrictions translate to certain responsibilities for you if you distribute copies of the library or if you modify it.

For example, if you distribute copies of the library, whether gratis or for a fee, you must give the recipients all the rights that we gave you. You must make sure that they, too, receive or can get the source code. If you link other code with the library, you must provide complete object files to the recipients, so that they can relink them with the library after making changes to the library and recompiling it. And you must show them these terms so they know their rights.

We protect your rights with a two-step method: (1) we copyright the library, and (2) we offer you this license, which gives you legal permission to copy, distribute and/or modify the library.

To protect each distributor, we want to make it very clear that there is no warranty for the free library. Also, if the library is modified by someone else and passed on, the recipients should know that what they have is not the original version, so that the original author's reputation will not be affected by problems that might be introduced by others.

Finally, software patents pose a constant threat to the existence of any free program. We wish to make sure that a company cannot effectively restrict the users of a free program by obtaining a restrictive license from a patent holder. Therefore, we insist that any patent license obtained for a version of the library must be consistent with the full freedom of use specified in this license.

Most GNU software, including some libraries, is covered by the ordinary GNU General Public License. This license, the GNU Lesser General Public License, applies to certain designated libraries, and is quite different from the ordinary General Public License. We use this license for certain libraries in order to permit linking those libraries into non-free programs.

When a program is linked with a library, whether statically or using a shared library, the combination of the two is legally speaking a combined work, a derivative of the original library. The ordinary General Public License therefore permits such linking only if the entire combination fits its criteria of freedom. The Lesser General Public License permits more lax criteria for linking other code with the library.

We call this license the "Lesser" General Public License because it does less to protect the user's freedom than the ordinary General Public License. It also provides other free software developers less of an advantage over competing non-free programs. These disadvantages are the reason we use the ordinary General Public License for many libraries. However, the Lesser license provides advantages in certain special circumstances.

For example, on rare occasions, there may be a special need to encourage the widest possible use of a certain library, so that it becomes a de-facto standard. To achieve this, non-free programs must be allowed to use the library. A more frequent case is that a free library does the same job as widely used non-free libraries. In this case, there is little to gain by limiting the free library to free software only, so we use the Lesser General Public License.

In other cases, permission to use a particular library in non-free programs enables a greater number of people to use a large body of free software. For example, permission to use the GNU C Library in non-free programs enables many more people to use the whole GNU operating system, as well as its variant, the GNU/Linux operating system.

Although the Lesser General Public License is less protective of the users' freedom, it does ensure that the user of a program that is linked with the Library has the freedom and the wherewithal to run that program using a modified version of the Library.

The precise terms and conditions for copying, distribution and modification follow. Pay close attention to the difference between a "work based on the library" and a "work that uses the library". The former contains code derived from the library, whereas the latter must be combined with the library in order to run.

#### TERMS AND CONDITIONS FOR COPYING, DISTRIBUTION AND MODIFICATION

0. This License Agreement applies to any software library or other program which contains a notice placed by the copyright holder or other authorized party saying it may be distributed under the terms of this Lesser General Public License (also called "this License"). Each licensee is addressed as "you".

A "library" means a collection of software functions and/or data prepared so as to be conveniently linked with application programs (which use some of those functions and data) to form executables.

The "Library", below, refers to any such software library or work which has been distributed under these terms. A "work based on the Library" means either the Library or any derivative work under copyright law: that is to say, a work containing the Library or a portion of it, either verbatim or with modifications and/or translated straightforwardly into another language. (Hereinafter, translation is included without limitation in the term "modification".)

"Source code" for a work means the preferred form of the work for making modifications to it. For a library, complete source code means all the source code for all modules it contains, plus any associated interface definition files, plus the scripts used to control compilation and installation of the library.

Activities other than copying, distribution and modification are not covered by this License; they are outside its scope. The act of running a program using the Library is not restricted, and output from such a program is covered only if its contents constitute a work based on the Library (independent of the use of the Library in a tool for writing it). Whether that is true depends on what the Library does and what the program that uses the Library does.

1. You may copy and distribute verbatim copies of the Library's complete source code as you receive it, in any medium, provided that you conspicuously and appropriately publish on each copy an appropriate copyright notice and disclaimer of warranty; keep intact all the notices that refer to this License and to the absence of any warranty; and distribute a copy of this License along with the Library.

You may charge a fee for the physical act of transferring a copy, and you may at your option offer warranty protection in exchange for a fee.

2. You may modify your copy or copies of the Library or any portion of it, thus forming a work based on the Library, and copy and distribute such modifications or work under the terms of Section 1 above, provided that you also meet all of these conditions:

- a) The modified work must itself be a software library.
- b) You must cause the files modified to carry prominent notices stating that you changed the files and the date of any change.
- c) You must cause the whole of the work to be licensed at no charge to all third parties under the terms of this License.
- d) If a facility in the modified Library refers to a function or a table of data to be supplied by an application program that uses the facility, other than as an argument passed when the facility is invoked, then you must make a good faith effort to ensure that, in the event an application does not supply such function or table, the facility still operates, and performs whatever part of its purpose remains meaningful.

(For example, a function in a library to compute square roots has a purpose that is entirely well-defined independent of the application. Therefore, Subsection 2d requires that any application-supplied function or table used by this function must be optional: if the application does not supply it, the square root function must still compute square roots.)

These requirements apply to the modified work as a whole. If identifiable sections of that work are not derived from the Library, and can be reasonably considered independent and separate works in themselves, then this License, and its terms, do not apply to those sections when you distribute them as separate works. But when you distribute the same sections as part of a whole which is a work based on the Library, the distribution of the whole must be on the terms of this License, whose permissions for other licensees extend to the entire whole, and thus to each and every part regardless of who wrote it.

Thus, it is not the intent of this section to claim rights or contest your rights to work written entirely by you; rather, the intent is to exercise the right to control the distribution of derivative or collective works based on the Library.

In addition, mere aggregation of another work not based on the Library with the Library (or with a work based on the Library) on a volume of a storage or distribution medium does not bring the other work under the scope of this License.

3. You may opt to apply the terms of the ordinary GNU General Public License instead of this License to a given copy of the Library. To do this, you must alter all the notices that refer to this License, so that they refer to the ordinary GNU General Public License, version 2, instead of to this License. (If a newer version than version 2 of the ordinary GNU General Public License has appeared, then you can specify that version instead if you wish.) Do not make any other change in these notices.

Once this change is made in a given copy, it is irreversible for that copy, so the ordinary GNU General Public License applies to all subsequent copies and derivative works made from that copy.

This option is useful when you wish to copy part of the code of the Library into a program that is not a library.

4. You may copy and distribute the Library (or a portion or derivative of it, under Section 2) in object code or executable form under the terms of Sections 1 and 2 above provided that you accompany it with the complete corresponding machine-readable source code, which must be distributed under the terms of Sections 1 and 2 above on a medium customarily used for software interchange.

If distribution of object code is made by offering access to copy from a designated place, then offering equivalent access to copy the source code from the same place satisfies the requirement to distribute the source code, even though third parties are not compelled to copy the source along with the object code.

5. A program that contains no derivative of any portion of the Library, but is designed to work with the Library by being compiled or linked with it, is called a "work that uses the Library". Such a work, in isolation, is not a derivative work of the Library, and therefore falls outside the scope of this License.

However, linking a "work that uses the Library" with the Library creates an executable that is a derivative of the Library (because it contains portions of the Library), rather than a "work that uses the library". The executable is therefore covered by this License. Section 6 states terms for distribution of such executables.

When a "work that uses the Library" uses material from a header file that is part of the Library, the object code for the work may be a derivative work of the Library even though the source code is not. Whether this is true is especially significant if the work can be linked without the Library, or if the work is itself a library. The threshold for this to be true is not precisely defined by law.

If such an object file uses only numerical parameters, data structure layouts and accessors, and small macros and small inline functions (ten lines or less in length), then the use of the object file is unrestricted, regardless of whether it is legally a derivative work. (Executables containing this object code plus portions of the Library will still fall under Section 6.)

Otherwise, if the work is a derivative of the Library, you may distribute the object code for the work under the terms of Section 6. Any executables containing that work also fall under Section 6, whether or not they are linked directly with the Library itself.

6. As an exception to the Sections above, you may also combine or link a "work that uses the Library" with the Library to produce a work containing portions of the Library, and distribute that work under terms of your choice, provided that the terms permit modification of the work for the customer's own use and reverse engineering for debugging such modifications.

You must give prominent notice with each copy of the work that the Library is used in it and that the Library and its use are covered by this License. You must supply a copy of this License. If the work during execution displays copyright notices, you must include the copyright notice for the Library among them, as well as a reference directing the user to the copy of this License. Also, you must do one of these things:

- a) Accompany the work with the complete corresponding machine-readable source code for the Library including whatever changes were used in the work (which must be distributed under Sections 1 and 2 above); and, if the work is an executable linked with the Library, with the complete machine-readable "work that uses the Library", as object code and/or source code, so that the user can modify the Library and then relink to produce a modified executable containing the modified Library. (It is understood that the user who changes the contents of definitions files in the Library will not necessarily be able to recompile the application to use the modified definitions.)
- b) Use a suitable shared library mechanism for linking with the Library. A suitable mechanism is one that (1) uses at run time a copy of the library already present on the user's computer system, rather than copying library functions into the executable, and (2) will operate properly with a modified version of the library, if the user installs one, as long as the modified version is interface-compatible with the version that the work was made with.
- c) Accompany the work with a written offer, valid for at least three years, to give the same user the materials specified in Subsection 6a, above, for a charge no more than the cost of performing this distribution.
- d) If distribution of the work is made by offering access to copy from a designated place, offer equivalent access to copy the above specified materials from the same place.
- e) Verify that the user has already received a copy of these materials or that you have already sent this user a copy.

For an executable, the required form of the "work that uses the Library" must include any data and utility programs needed for reproducing the executable from it. However, as a special exception, the materials to be distributed need not include anything that is normally distributed (in either source or binary form) with the major components (compiler, kernel, and so on) of the operating system on which the executable runs, unless that component itself accompanies the executable.

It may happen that this requirement contradicts the license restrictions of other proprietary libraries that do not normally accompany the operating system. Such a contradiction means you cannot use both them and the Library together in an executable that you distribute.

7. You may place library facilities that are a work based on the Library side-by-side in a single library together with other library facilities not covered by this License, and distribute such a combined library, provided that the separate distribution of the work based on the Library and of the other library facilities is otherwise permitted, and provided that you do these two things:

a) Accompany the combined library with a copy of the same work based on the Library, uncombined with any other library facilities. This must be distributed under the terms of the Sections above.

b) Give prominent notice with the combined library of the fact that part of it is a work based on the Library, and explaining where to find the accompanying uncombined form of the same work.

8. You may not copy, modify, sublicense, link with, or distribute the Library except as expressly provided under this License. Any attempt otherwise to copy, modify, sublicense, link with, or distribute the Library is void, and will automatically terminate your rights under this License. However, parties who have received copies, or rights, from you under this License will not have their licenses terminated so long as such parties remain in full compliance.

9. You are not required to accept this License, since you have not signed it. However, nothing else grants you permission to modify or distribute the Library or its derivative works. These actions are prohibited by law if you do not accept this License. Therefore, by modifying or distributing the Library (or any work based on the Library), you indicate your acceptance of this License to do so, and all its terms and conditions for copying, distributing or modifying the Library or works based on it.

10. Each time you redistribute the Library (or any work based on the Library), the recipient automatically receives a license from the original licensor to copy, distribute, link with or modify the Library subject to these terms and conditions. You may not impose any further restrictions on the recipients' exercise of the rights granted herein. You are not responsible for enforcing compliance by third parties with this License.

11. If, as a consequence of a court judgment or allegation of patent infringement or for any other reason (not limited to patent issues), conditions are imposed on you (whether by court order, agreement or otherwise) that contradict the conditions of this License, they do not excuse you from the conditions of this License. If you cannot distribute so as to satisfy simultaneously your obligations under this License and any other pertinent obligations, then as a consequence you may not distribute the Library at all. For example, if a patent license would not permit royalty-free redistribution of the Library by all those who receive copies directly or indirectly through you, then the only way you could satisfy both it and this License would be to refrain entirely from distribution of the Library.

If any portion of this section is held invalid or unenforceable under any particular circumstance, the balance of the section is intended to apply, and the section as a whole is intended to apply in other circumstances.

It is not the purpose of this section to induce you to infringe any patents or other property right claims or to contest validity of any such claims; this section has the sole purpose of protecting the integrity of the free software distribution system which is implemented by public license practices. Many people have made generous contributions to the wide range of software distributed through that system in reliance on consistent application of that system; it is up to the author/donor to decide if he or she is willing to distribute software through any other system and a licensee cannot impose that choice.

This section is intended to make thoroughly clear what is believed to be a consequence of the rest of this License.

12. If the distribution and/or use of the Library is restricted in certain countries either by patents or by copyrighted interfaces, the original copyright holder who places the Library under this License may add an explicit geographical distribution limitation excluding those countries, so that distribution is permitted only in or among countries not thus excluded. In such case, this License incorporates the limitation as if written in the body of this License.

13. The Free Software Foundation may publish revised and/or new versions of the Lesser General Public License from time to time. Such new versions will be similar in spirit to the present version, but may differ in detail to address new problems or concerns.

Each version is given a distinguishing version number. If the Library specifies a version number of this License which applies to it and "any later version", you have the option of following the terms and conditions either of that version or of any later version published by the Free Software Foundation. If the Library does not specify a license version number, you may choose any version ever published by the Free Software Foundation.

14. If you wish to incorporate parts of the Library into other free programs whose distribution conditions are incompatible with these, write to the author to ask for permission. For software which is copyrighted by the Free Software Foundation, write to the Free Software Foundation; we sometimes make exceptions for this. Our decision will be guided by the two goals of preserving

the free status of all derivatives of our free software and of promoting the sharing and reuse of software generally.

#### NO WARRANTY

15. BECAUSE THE LIBRARY IS LICENSED FREE OF CHARGE, THERE IS NO WARRANTY FOR THE LIBRARY, TO THE EXTENT PERMITTED BY APPLICABLE LAW. EXCEPT WHEN OTHERWISE STATED IN WRITING THE COPYRIGHT HOLDERS AND/OR OTHER PARTIES PROVIDE THE LIBRARY "AS IS" WITHOUT WARRANTY OF ANY KIND, EITHER EXPRESSED OR IMPLIED, INCLUDING, BUT NOT LIMITED TO, THE IMPLIED WARRANTIES OF MERCHANTABILITY AND FITNESS FOR A PARTICULAR PURPOSE. THE ENTIRE RISK AS TO THE QUALITY AND PERFORMANCE OF THE LIBRARY IS WITH YOU. SHOULD THE LIBRARY PROVE DEFECTIVE, YOU ASSUME THE COST OF ALL NECESSARY SERVICING, REPAIR OR CORRECTION.

16. IN NO EVENT UNLESS REQUIRED BY APPLICABLE LAW OR AGREED TO IN WRITING WILL ANY COPYRIGHT HOLDER, OR ANY OTHER PARTY WHO MAY MODIFY AND/OR REDISTRIBUTE THE LIBRARY AS PERMITTED ABOVE, BE LIABLE TO YOU FOR DAMAGES, INCLUDING ANY GENERAL, SPECIAL, INCIDENTAL OR CONSEQUENTIAL DAMAGES ARISING OUT OF THE USE OR INABILITY TO USE THE LIBRARY (INCLUDING BUT NOT LIMITED TO LOSS OF DATA OR DATA BEING RENDERED INACCURATE OR LOSSES SUSTAINED BY YOU OR THIRD PARTIES OR A FAILURE OF THE LIBRARY TO OPERATE WITH ANY OTHER SOFTWARE), EVEN IF SUCH HOLDER OR OTHER PARTY HAS BEEN ADVISED OF THE POSSIBILITY OF SUCH DAMAGES.

#### END OF TERMS AND CONDITIONS

## C.2 License for Ookii.Dialogs.Wpf Library

### BSD 3-Clause License

Copyright (c) C. Augusto Proiete 2018-2021  
 Copyright (c) Sven Groot 2009-2018  
 All rights reserved.

Redistribution and use in source and binary forms, with or without modification, are permitted provided that the following conditions are met:

1. Redistributions of source code must retain the above copyright notice, this list of conditions and the following disclaimer.
2. Redistributions in binary form must reproduce the above copyright notice, this list of conditions and the following disclaimer in the documentation and/or other materials provided with the distribution.
3. Neither the name of the copyright holder nor the names of its contributors may be used to endorse or promote products derived from this software without specific prior written permission.

THIS SOFTWARE IS PROVIDED BY THE COPYRIGHT HOLDERS AND CONTRIBUTORS "AS IS" AND ANY EXPRESS OR IMPLIED WARRANTIES, INCLUDING, BUT NOT LIMITED TO, THE IMPLIED WARRANTIES OF MERCHANTABILITY AND FITNESS FOR A PARTICULAR PURPOSE ARE DISCLAIMED. IN NO EVENT SHALL THE COPYRIGHT HOLDER OR CONTRIBUTORS BE LIABLE FOR ANY DIRECT, INDIRECT, INCIDENTAL, SPECIAL, EXEMPLARY, OR CONSEQUENTIAL DAMAGES (INCLUDING, BUT NOT LIMITED TO, PROCUREMENT OF SUBSTITUTE GOODS OR SERVICES; LOSS OF USE, DATA, OR PROFITS; OR BUSINESS INTERRUPTION) HOWEVER CAUSED AND ON ANY THEORY OF LIABILITY, WHETHER IN CONTRACT, STRICT LIABILITY, OR TORT (INCLUDING NEGLIGENCE OR OTHERWISE) ARISING IN ANY WAY OUT OF THE USE OF THIS SOFTWARE, EVEN IF ADVISED OF THE POSSIBILITY OF SUCH DAMAGE.

# **Pacific Northwest National Laboratory**

902 Battelle Boulevard  
P.O. Box 999  
Richland, WA 99354  
1-888-375-PNNL (7665)

[\*\*www.pnnl.gov\*\*](http://www.pnnl.gov)

**UNCLASSIFIED**